moooi

Heracleum III Endless

BERTJAN POT | POWERED THROUGH ELECTROSANDWICH® BY MARCEL WANDERS



Forever blossoming, Heracleum III Endless by Bertjan Pot connects seamlessly for limitless designs. Slender branches light leaf-shaped lenses, powered with Electrosandwich® by Marcel Wanders Studio. Perfect for bespoke spaces, it is endlessly connectable – straight, 90° or 135°. Available in four colours and compatible with the Wireless Wall Switch.

Detailing

The Heracleum III Endless is powered by Electrosandwich, a coating of conductive layers on the branches that creates a clean silhouette.

Colours



Copper



Green



Nickel



White

Heracleum III Endless

Dimensions

116 cm | 45.7"



Product

WIDTH 116cm | 45.7" **HEIGHT** 37cm | 14.6" **DEPTH** 57cm | 22.4"

WEIGHT NETTO 4.5kg | 9.92lbs

Packaging

WIDTH 72cm | 28.3" **HEIGHT** 53cm | 20.9" **CUBAGE** 0.6m³ | 21.02ft³ **LENGTH** 156cm | 61.4"

weight 6.5kg | 14.33lbs

Technical CE / UL

MATERIAL

Metal wire frame, polycarbonate lenses, ultra thin suspension wire

LIGHTSOURCE TYPE LIGHTSOURCE INCLUDED

LED Yes

NUMBER OF LIGHTSOURCES INPUT VOLTAGE

45 120-250V

FREQUENCY MAX POWER CONSUMPTION

50/60 16W

LAMPHOLDERLIFETIMELED (Solid state)50000 hours

CABLE COLOURCABLE LENGTHTransparent with tinned cores400cm | 157.5"

ANOPY CHROM X

Pebble III in matching color, Pebble III Copper Coated, O.46 ABS, Pebble III Green Coated, ABS, Pebble III Nickel

Coated, ABS, Pebble III White Coated, ABS

0.4

2600 K (max)

LIGHT DIRECTIONAll directions

1180 lm

CRI

91

DIMMING & LIGHTING CONTROL

DALI dt6, Push / Pulse dim on Line Voltage, Wireless Wall Switch (dimmer), Mains / ELV dimming is not possible, 0-10V

See last page for more information about the dimming possibilities.





Dimming & Lighting Control

DALL dt6

The luminaire is dimmable by integrating it into a DALI network. This is an universal and professional standard in home automation systems with endless control possibilities and ease. We advise to hire a professional to integrate the luminaire into your DALI network.

Compatible models: Heracleum III Endless CCC, Heracleum III Endless CE, Heracleum III Endless UL

Push / Pulse dim on Line Voltage

The luminaire is dimmable by using an external momentary switch or pushbutton switch. The switch is usually mounted on an existing wall socket. In some cases a Phase or Control wire needs to be added to your home's wiring. The switch should be suitable for use with line voltage and of the type 'normal off - momentary on'. The luminaire dims perfectly when the switch makes and holds contact. A short press switches between on and off.

Compatible models: Heracleum III Endless CCC, Heracleum III Endless CE, Heracleum III Endless UL

Wireless Wall Switch (dimmer)

With our Wireless Wall Switch, you'll have full control over your Moooi lighting design with one touch. Our Wireless Wall Switch comprises two components, a wall switch and radio device to put in the canopy of your Moooi lighting design. The wall switch can be integrated in System 55 or Decora style wall switches. The Wireless Wall Switch communicates via Bluetooth with the radio device in the luminaires canopy. Within moments you can enjoy full and fluent dimming, all the way to dark.

Compatible models: Heracleum III Endless CCC, Heracleum III Endless CE, Heracleum III Endless UL

Mains / ELV dimming is not possible

Mains and/or ELV dimming is not possible. The wireless wall switch is advised for dimming in this case.

Compatible models: Heracleum III Endless CCC, Heracleum III Endless CE, Heracleum III Endless UL

0-10V

The luminaire is dimmable by using an either internally mounted or externally placed 0-10V dimmer switch. 0-10V is a dimming system widely used in some parts of the world, for example in North-America. This method will need its own wiring. Dimming quality is perfect, without flicker, the range can be limited and the luminaire can be dimmed to off.

Compatible models: Heracleum III Endless CE, Heracleum III Endless UL