

m o o o i


Raimond II Zafu

RAIMOND PUTS



The Raimond Zafu creates an extra-terrestrial effect with its elliptical shape and tiny LED-lights. Like its spherical family members, the Raimond Zafu is made from the same elegant metal strips and mathematical ingredients. The name Zafu comes from the transcendental shape inspired by designer Raimond Puts' meditation cushion. Raimond Zafu is compatible with our Wireless Wall Switch, for quick and easy dimming that gives you full control over the light output.

Detailing



With the optional Wireless Wall Switch, dimming is made even easier. With just one click you control the lights and mood.

Colours




Stainless steel

Raimond II Zafu / Raimond II Zafu, 75

Dimensions

75 cm | 29.5"



Product

WIDTH 75cm | 29.5"
HEIGHT 39cm | 15.4"
DEPTH 75cm | 29.5"
DIAMETER 75cm | 29.5"
WEIGHT NETTO 2kg | 4.4lbs

Packaging

WIDTH 83cm | 32.7"
HEIGHT 39cm | 15.4"
CUBAGE 0.27m³ | 9.49ft³
LENGTH 83cm | 32.7"
WEIGHT 5kg | 11.02lbs

Technical UL / CE

ADDITIONAL

Compatible with our Wireless Wall Switch, for quick and easy dimming that gives you full control over the light output.

MATERIAL

Stainless Steel Ellipsoid (indoor use, not resistant to marine environemts) with PMMA lenses

ENERGY LABEL

B

LIGHTSOURCE TYPE

LED

LIGHTSOURCE INCLUDED

Yes

NUMBER OF LIGHTSOURCES

162

INPUT VOLTAGE

120-250V

FREQUENCY

50/60

MAX POWER CONSUMPTION

29W

LAMPHOLDER

LED (Solid state)

LIFETIME

50000 hours

CABLE COLOUR

Transparent with tinned cores

CABLE LENGTH

250cm | 98.4"

CANOPY

Pebble III Steel Coated, ABS

COLOUR TEMPERATURE

2500 K (max)

CRI

92

LIGHT DIRECTION

All directions

LIGHT OUTPUT

1062 lm

DIMMING & LIGHTING CONTROL

DALI dt6, Push / Pulse dim on Line Voltage, Wireless
Wall Switch (dimmer), Mains / ELV dimming is not
possible, 0-10V

See last page for more information about the dimming possibilities.



Dimming & Lighting Control

DALI dt6

The luminaire is dimmable by integrating it into a DALI network. This is an universal and professional standard in home automation systems with endless control possibilities and ease. We advise to hire a professional to integrate the luminaire into your DALI network.

Compatible models: Raimond II Zafu, 75 UL, Raimond II Zafu, 75 CE

Push / Pulse dim on Line Voltage

The luminaire is dimmable by using an external momentary switch or pushbutton switch. The switch is usually mounted on an existing wall socket. In some cases a Phase or Control wire needs to be added to your home's wiring. The switch should be suitable for use with line voltage and of the type 'normal off - momentary on'. The luminaire dims perfectly when the switch makes and holds contact. A short press switches between on and off.

Compatible models: Raimond II Zafu, 75 UL, Raimond II Zafu, 75 CE

Wireless Wall Switch (dimmer)

With our Wireless Wall Switch, you'll have full control over your Moooi lighting design with one touch. Our Wireless Wall Switch comprises two components, a wall switch and radio device to put in the canopy of your Moooi lighting design. The wall switch can be integrated in System 55 or Decora style wall switches. The Wireless Wall Switch communicates via Bluetooth with the radio device in the luminaires canopy. Within moments you can enjoy full and fluent dimming, all the way to dark.

Compatible models: Raimond II Zafu, 75 UL, Raimond II Zafu, 75 CE

Mains / ELV dimming is not possible

Mains and/or ELV dimming is not possible. The wireless wall switch is advised for dimming in this case.

Compatible models: Raimond II Zafu, 75 UL, Raimond II Zafu, 75 CE

0-10V

The luminaire is dimmable by using an either internally mounted or externally placed 0-10V dimmer switch. 0-10V is a dimming system widely used in some parts of the world, for example in North-America. This method will need its own wiring. Dimming quality is perfect, without flicker, the range can be limited and the luminaire can be dimmed to off.

Compatible models: Raimond II Zafu, 75 UL, Raimond II Zafu, 75 CE
